Casambi || receiver | 12-24V | 6A | TW/RGB/RGBW/1..4CH.

ARTICLE NUMBER: 214-205

View this product in our webshop

CASAMBI



17.11.2026 - Disclaimer: information subject to change.

Bluetooth LED controller for constant voltage LED lighting. Suitable for RGB, RGBW, tuneable white and single-colour applications. Operated via the Casambi app or a compatible remote. Maximum output power: 144 W at 24V.

Key product features

- **Number of colour channels:** 4
- **Output voltage (V):** 12 – 24
- **Input voltage (V):** 12 – 24
- **Max. output current (A):** 2
- **Type of control:** Casambi
- **Control type:** Constant voltage
- **Number of zones:** 4


Technical specifications:

Product Name	Casambi || receiver | 12-24V | 6A | TW/RGB/RGBW/1..4CH.
Ean	8714984935952
Outer box qty	1st
Model	Dynamic
Housing	Plastic housing
Programmable	Yes
Max. output current	2A
Output voltage	12 - 24V
Suitable for outdoor use	No
Degree of protection (IP)	IP20
Length	72.6mm
Width	30mm
Height	18mm
Number of zones	4
Number of colour channels	4, RGBW

17.11.2026 - Disclaimer: information subject to change.

Suitable for surface mounting	Yes
Suitable for built-in mounting	No
Input voltage	12 - 24V
Control method	Casambi
DIN-rail mounting	No
Brand	Tronix Lighting
Compatible with Casambi	Yes
Control type	Constant voltage
Warranty	5 years





17.11.2026 - Disclaimer: information subject to change.