Casambi | dimmer | 230V | 200W | recessed | 230V push dim

ARTICLE NUMBER: 214-219

View this product in our webshop

CASAMBI



17.11.2026 - Disclaimer: information subject to change.

Compact Casambi trailing edge dimmer module for 100–240 V AC, controllable via the Casambi app or a 230 V push button. Suitable for 2-wire and 3-wire installations. Compatible with dimmable LEDs, halogen lamps and retrofit projects.

Key product features


- **Light value memory:** Yes
- **Applicable with button:** Yes
- **Mounting method:** Built-in
- **Control voltage (V):** 100–240
- **Dimming phase cut-off (trailing edge):** Yes
- **Max. switching power LED (W):** 200
- **Control method:** Casambi

Technical specifications:

Product Name	Casambi | dimmer | 230V | 200W | recessed | 230V push dim
Ean	8714984952287
Outer box qty	100st
Colour	White
Connection type	Screwed terminal
Operating method	Radio frequency (RF)
Control method	Casambi
Mounting method	Built-in
Material	Plastic
Material quality	Thermoplastic
Applicable with presence indicator	Yes
Suitable for degree of protection (IP)	IP20
Applicable with movement sensor	Yes
Applicable with button	Yes
Applicable with transmission button	Yes

17.11.2026 - Disclaimer: information subject to change.

Applicable with time switch/timer	Yes
Nominal voltage	100 - 240V
Control voltage	100 - 240V
Min. depth of built-in installation box	18mm
Min. brightness controllable	Yes
Max. switching power LED	200W
Light value memory	Yes
Halogen free	Yes
RAL-number (similar)	9016
Core cross section	0.75 - 2.5mm??
Warranty	5 years



17.11.2026 - Disclaimer: information subject to change.