Constant current receiver || 1 channel x 700mA

ARTICLE NUMBER: 214-148

View this product in our webshop



17.11.2026 - Disclaimer: information subject to change.

1-channel RF receiver for single-colour LED lighting (12–36V DC, max. 8 A). Supports wireless switching and dimming via remote control or push switch. Requires external power supply.

Key product features

- **Type of control:** RF
- **Number of colour channels:** 1
- **Input voltage (V):** 12 – 36
- **Max. output current (A):** 0.7
- **Control type:** Constant current

Technical specifications:

Product Name	Constant current receiver || 1 channel x 700mA
Ean	8714984915077
Outer box qty	1st
Model	Dynamic
Housing	Plastic housing
Programmable	No
Max. output current	0.7A
Output voltage	12 - 36V
Suitable for outdoor use	No
Degree of protection (IP)	IP20
Length	101mm
Width	36mm
Height	21mm
Number of zones	1
Number of colour channels	1, Single Colour
Suitable for surface mounting	Yes
Suitable for built-in mounting	No

17.11.2026 - Disclaimer: information subject to change.

Input voltage	12 - 36V
Control method	RF
DIN-rail mounting	No
Brand	Tronix Lighting
Compatible with Casambi	No
Control type	Constant current
Warranty	5 years