# Constant voltage receiver | 1 channel x 8 amp??re

ARTICLE NUMBER: 214-147

View this product in our webshop




17.11.2026 - Disclaimer: information subject to change.

1-channel RF receiver for single-colour LED lighting (12–36V DC, max. 8 A). Supports wireless switching and dimming via remote control or push switch. External power supply required.

**Key product features**

- **Type of control:** RF
- **Number of colour channels:** 1
- **Output voltage (V):** 12 – 36
- **Input voltage (V):** 12 – 36
- **Max. output current (A):** 8
- **Control type:** Constant voltage

**Technical specifications:**

| | |
|---|---|
| Product Name | Constant voltage receiver \| 1 channel x 8 amp??re |
| Ean | 8714984915060 |
| Outer box qty | 1st |
| Model | Dynamic |
| Housing | Plastic housing |
| Programmable | No |
| Max. output current | 8A |
| Output voltage | 12 - 36V |
| Suitable for outdoor use | No |
| Degree of protection (IP) | IP20 |
| Length | 101mm |
| Width | 36mm |
| Height | 21mm |
| Number of zones | 1 |
| Number of colour channels | 1, Single Colour |
| Suitable for surface mounting | Yes |

17.11.2026 - Disclaimer: information subject to change.

| | |
|---|---|
| Suitable for built-in mounting | No |
| Input voltage | 12 - 36V |
| Control method | RF |
| DIN-rail mounting | No |
| Brand | Tronix Lighting |
| Compatible with Casambi | No |
| Control type | Constant voltage |
| Warranty | 5 years |