# LED driver | 150/175/200/230/260mA | max 40V/11W EU plug

ARTICLE NUMBER: 215-160

View this product in our webshop




17.11.2026 - Disclaimer: information subject to change.

The ideal LED driver when it comes to a good balance between an attractive price and excellent performance. Thanks to the focus on user-friendliness, you not only have a power supply that works with a wide selection of lamps, but also a product that you can rely on for years to come.

**Features**

- Constant current output
- Freely adjustable power output from 6 to 11 watts
- Very compact size for easy placement
- IP20 protected


**Technical specifications:**

| | |
|---|---|
| Product Name | LED driver \| 150/175/200/230/260mA \| max 40V/11W EU plug |
| Ean | 8714984947481 |
| Outer box qty | 50st |
| Housing | Plastic housing |
| Model | Static |
| Output voltage | 30 - 40V |
| Output current | 150 - 260mA |
| Suitable for outdoor use | No |
| Suitable for DC-voltage (primary side) | No |
| Output power | 7 - 11W |
| Degree of protection (IP) | IP20 |
| Length | 103mm |
| Width | 39mm |
| Height | 28mm |
| Power consumption | 10W |
| Input voltage | 200 - 240V |

17.11.2026 - Disclaimer: information subject to change.

| | |
|---|---|
| Frequency input voltage | 50 - 60Hz |
| Overload protection | Yes |
| Overtemperature protection | Yes |
| Control method | Non-dimmable |
| Short-circuit protected | Yes |
| Ambient temperature | -20 - 45??C |
| Driver lifetime | 50000h |
| DIN-rail mounting | No |
| Brand | Tronix Lighting |
| Dimmable | No |
| Emergency power supply system | None |
| Control type | Constant current |
| Warranty | 3 years |






17.11.2026 - Disclaimer: information subject to change.