RF | controller | SC | 100-240V trailing edge

ARTICLE NUMBER: 213-026

View this product in our webshop



17.11.2026 - Disclaimer: information subject to change.

This RF, 0/1–10V and push-dim AC trailing edge dimmer offers versatile control of 230V light sources. One compact solution for both wireless and wired dimming.


Key product features

- **Control method:** RF
- **Number of colour channels:** 1
- **Output voltage (V):** 100 – 240
- **Input voltage (V):** 100 – 240
- **Max. output current (A):** 2
- **Suitable for surface mounting:** Yes

Technical specifications:

Product Name	RF | controller | SC | 100-240V trailing edge
Ean	8714984956254
Outer box qty	1st
Colour	White
Connection type	Screwed terminal
Operating method	Radio frequency (RF)
Control method	RF
Mounting method	Surface mounted
Material	Plastic
Material quality	Thermoplastic
Applicable with presence indicator	Yes
Suitable for degree of protection (IP)	IP20
Applicable with movement sensor	Yes
Applicable with button	Yes
Applicable with transmission button	Yes
Applicable with time switch/timer	Yes

Nominal voltage	100 - 240V
Control voltage	100 - 240V
Min. brightness controllable	Yes
Max. switching power LED	300W
Light value memory	Yes
Halogen free	Yes
RAL-number (similar)	9016
Core cross section	0.75 - 2.5mm??
Warranty	5 years



17.11.2026 - Disclaimer: information subject to change.